



COSMO 2000

2000FT WIRELESS VIDEO TRANSMISSION PLAY BACK WITHOUT INTERRUPTION

COSMO 2000 SUPPORT ARRI MINI CAMERA THAT YOU CAN PLAYBACK VIDEO
WITHOUT ANY DELAY, SAVING YOUR TIME TO SHOOT A FILM.

- Transmission Range: 2000ft
- Channel Selection:0-4/Outside USA:0-9
- USB Firmware Upgrade
- No Compression, No Latency
- Point to Point & Broadcast Mode

- 3G-SDI In/Loop Out/, HDMI In/Out
- 5GHz ISM Frequency Band
- 3G-SDI Level B
- Image Encryption Function

Packing List



Hard Case*1



5 GHz Antennas*8



Magic Arm*1



Crab Clamp*1



D-tap to Lemo Cables*2



Transmitter*1



Receiver*1



User Manual*1

Spec

	Transmitter	Receiver
Interface	SDI Input (BNC female); SDI Loop Out (BNC female) HDMI Input (Type A female); 2 Antenna Port (RP-SMA male) DC Input (4pin LEMO female); Mini USB; 3.5mm Stereo In	SDI Output; SDI2 Output HDMI Output (Type A female); 5 Antenna Port (RP-SMA male) DC Input (4pin LEMO female); Mini USB
Supply Voltage Range	7-36V DC	7-36V DC
Power Consumption	<9W	<8W
Weight	315g	520g
Size	(LxWxH): 116x 68 x 25mm, not include antennas and battery plate	(LxWxH): 158x 102 x 25mm, not include antennas and battery plate
Input Video Format	HDMI: 480p60, 576p50, 720p50/59.94/60, 1080i50/59.94/60, 1080p23.98/24/25/29.97/30/50/59.94/60; HDMI Type A; SDI: 3G, HD, and SD-SDI (auto-selected); SMPTE-259/274/292/296/372/424/425; 1x BNC; 1x BNC Loopout;	/
Output Video Format	/	HDMI: 480p60, 576p50, 720p50/59.94/60, 1080i50/59.94/60, 1080p23.98/24/25/29.97/30/50/59.94/60; HDMI Type A; SDI: 3G, HD, and SD-SDI (auto-selected); SMPTE-259/274/292/296/372/424/425; 2x BNC output;
Input Audio	SDI embedded 2 channel 24 bit/48KHz	/
Output Audio	/	SDI embedded 2 channel 24 bit/48KHz
Frequency Band	5.1-5.9GHz, configurable with China, North America, Europe, etc	5.1-5.9GHz, configurable with China, North America, Europe, etc
Modulation Mode	OFDM-16QAM	OFDM-16QAM
Transmission Power	Maximum 18dBm	/
Receiver Sensitivity	/	-75dBm
Occupied Bandwidth	40MHz	40MHz